

LG CordZero®

A9

A9ESSENTIAL Product Sheet



Powerful Suction

Smart Inverter Motor® P9



Dual PowerPack

Up to 80 minutes run time¹
with two interchangeable batteries



Thumb Touch Control

Easy on, off and power level
selection.



Floor-Standing Dock

Conveniently position on the
floor.



DESIGN & CONVENIENCE

Colour	Black
Vacuum Type	Cordless Handstick
Convenience	
Control Type	Button
Telescopic Pipe	✓ (4 Lengths)
Dust Bin Capacity	0.44L
Convert to Handheld	✓
Charging	
Charging Dock	✓
Wall Mount Option	✓
Floor-Standing Option	✓

PERFORMANCE

Motor Technology	Smart Inverter Motor® P9
Cyclone Technology	Axial Turbo Cyclone®
Suction	
Power Modes	3 Modes (Normal, Power, Turbo)
Max Suction Power	Up to 140W (In Turbo Mode)
Battery	
Batteries Included	2
Battery Type	Lithium-Ion
Battery Indicator	✓ (3 Step)
Charging Time	3.5 hours per battery
Max Running Time	
Normal Mode <i>Without Power Drive Nozzle®</i>	Up to 40 minutes per battery
Normal Mode <i>With Power Drive Nozzle®</i>	Up to 30 minutes per battery
Power Mode	Up to 9 minutes per battery
Turbo Mode	Up to 6 minutes per battery
Filtration	
Technology	5 Step
Washable Filters	3 (Pre-Filter, Mesh, Fine Dust Exhaust)
Noise (Turbo Mode)	86db

MOTORISED NOZZLES

Hard Floor Power Drive Nozzle®	Not Included
<i>A specialised tool for use on tiles and hardfloors.</i>	
Multi-Surface Power Drive Nozzle®	✓
<i>For use on carpets, tiles or hardfloors.</i>	
Bedding Power Punch®	Not Included
<i>For use in removing dirt from mattresses, sofas, cloth seats or other fabrics.</i>	

OTHER NOZZLES

Crevice Tool	✓	
Combination Tool	✓	
TOTAL CARE KIT	Flexible Crevice Tool	Not Included
	Multi Angle Tool	Not Included
	Hard Dirt Tool	Not Included
	Mattress Tool	Not Included
	Extendable Hose	Not Included
Accessories		
Spare Pre-Filter (Green)	✓	

DIMENSIONS

Packaging (W x D x H)	720mm x 295mm x 240mm
Weight (Hand Unit Only)	1.6kg
Weight(Incl. Multi-Surface Nozzle)	2.7kg

WARRANTY & COMPLIANCE

EAN	8806098337194
Handstick	2 Years Parts & Labour
Battery	12 Months Warranty
Smart Inverter Motor®	10 Years Warranty*
* 2 years parts and labour + 8 years on motor (parts only)	

DISCLAIMERS

¹ Up to 80 minutes run time when using 2 batteries in starting 'normal' mode without Power Drive Nozzle. Battery life may vary depending on settings and with use.

All product specifications are correct at time of printing. Specifications may change without prior notice. Customers are advised to check with your retailer before purchase.